

32GB Computer memory DDR3 for Fujitsu Primergy BX920 S3 LRDIMM



phs memory®

51,68 EUR

plus VAT

61,50 EUR

incl. VAT

in magazzino

<https://www.phs-memory.it>

Version: 05.09.2025 23:57

Your benefits

- ✓ verified quality memory
- ✓ 5 years warranty
Warranty details see last page
- ✓ 100% compatible
- ✓ free support on our hotline
- ✓ fast delivery

PHS-memory® - computer memory with 100% quality

- many years of IT competence
- Free support for optimal configuration and product selection
- High availability through professional warehouse management
- Fast delivery in throughout Europe
- Short response times and professional order processing due to full digitalization throughout the entire process with complete traceability
- Incoming goods inspection include checks of the DRAMs, PCBs and the programmed SPDs in order to exclude possible errors (Controlled BOM).
- PHS-memory® brand memories guarantee 100% compatibility to the specified system.
- PHS-memory® memories can be used together with existing memories in the device - depends on to the configuration rules of the system.
- The "fallback option" in the SPD of PHS-memory® allows DRAMs with higher clock rates to be operated together with older memory modules with lower clock rates within the system.
- Products with unique serial number for service and warranty
- Pre-sales and after-sales support by technically trained personnel

Memory Specification



Memory size	32GB
Memory technology	DDR3
ECC support	ja
JEDEC Norm	PC3L-10600L
DRAM Organization	2Gx4
Rank	4Rx4 (4DRx4 DDP)
Type	LRDIMM (ECC LR DIMM)
Number of pins	240 Pin DIMM
Memory data transfer rate	1333MHz @ CL9
Voltage	1,35 Volt
Speciality	DDP
Board dimensions	133,35 x 30 (LxB mm)
Operating temperature	0° C - 85° C
Storage temperature	-40° C - +95° C
RoHS compliant	Yes
SKU	SP159004
EAN	4055069306873

Note: The module specified in this datasheet is one of several possible configurations available under this part number.
Some details may differ from the specifications described here and the illustration, but have no negative influence on the functionality.

System Specifications

The memory is 100% compatible with this system:

System manufacturer	Fujitsu
Device type	Server
Device family	Primergy
Device series	BX900 Serie
Device name	Primergy BX920 S3
Maximum memory*	384GB
Number of memory sockets	12
Annotation	ECC UDIMM, RDIMM and LR DIMM can not be mixed in the server. With ECC UDIMM a maximum of 48GB, RDIMM a maximum of 192GB, LR DIMM a maximum of 384GB is possible

* The specifications for the maximum memory upgrade may differ from those of the manufacturer Fujitsu. Often the information given in the manual for the maximum memory upgrade is not up to date. New memory technologies, bios updates or newer software versions often allow the use of memory modules with a higher capacity than specified by the manufacturer with the same performance and stability.

Information on memory allocation

Which memory configuration is possible?

Our memory team will be happy to help you choose the right memory and configure your server.

Technologie	Board 6 Slot	Board 12 Slot
UDIMM ECC	24GB RAM	48GB RAM
RDIMM	96GB RAM	192GB RAM
LRDIMM	192GB RAM	384GB RAM

ECC DIMM, Registered DIMM and Load Reduced LRDIMM memory modules must not be mixed. Bei einer Aufrüstung sollten Sie deshalb wissen, welche memory bereits vorhanden sind, or komplett auf RDIMMcomputer memory upgrade.

Principles of memory assembly

- Die memorysteckplätze sind in 2er Gruppen organisiert
- Die verschiedenen 2er Steckplatzgruppen müssen nicht die gleichen Kapazitäten haben
- Es können nur die memorysteckplätze genutzt werden, bei denen die jeweilige CPU vorhanden ist.

Memory configuration for good system performance

- Verteilen Sie die memory gleichmäßig auf die memorysteckplätze and gleichmäßig auf die CPUs
- Wenn mehr als eine CPU vorhanden sind, sollten die memory pro CPU identisch (gespiegelt zur anderen CPU) bestückt werden.

Information on memory installation

- Turn off the system
- Remove the plug of the power supply unit (if connected)
- Remove the battery, according to the user manual of the system
- Always ground yourself before touching electronic components
- Protect the memory module from static voltages:
 - Do not touch the gold pins of the memory module
 - Only touch the sides of the memory module
 - Use a grounding strap and/or ESD glove if possible

General installation instructions are supplied by E-Mail.

Further memory options for Fujitsu Primergy BX920 S3

Size	SKU	Technology	Type	Number of pins	Brand	Reference no.
4GB	SP159003	DDR3	UDIMM ECC (ECC unbuffered)	240 Pin DIMM	PHS-memory®	S26361-F3694-L614
8GB	SP159007	DDR3	RDIMM (ECC Registered)	240 Pin DIMM	PHS-memory®	S26361-F3697-L615
8GB	SP465589	DDR3	UDIMM ECC (ECC unbuffered)	240 Pin DIMM	PHS-memory®	
16GB	SP159005	DDR3	RDIMM (ECC Registered)	240 Pin DIMM	PHS-memory®	S26361-F3697-L616
32GB	SP159004	DDR3	LRDIMM (ECC LR DIMM)	240 Pin DIMM	PHS-memory®	S26361-F3698-L617
32GB	SP464051	DDR3	RDIMM (ECC Registered)	240 Pin DIMM	PHS-memory®	

PHS-memory® warranty

Every PHS-memory® is equipped with a 5-years-warranty of perfect operation. If the RAM module is defective or fails within 5 years of purchase when used properly, you will receive an appropriate RAM module free of charge. If a suitable memory module is no longer available, we will refund the purchase price.

For more information on warranty and service please visit <https://www.phs-memory.it/-W5Y>



Contact Information

PHS-electronic gmbh
- www.phs-memory.it -
Karl-Götz-Str. 5
97424 Schweinfurt
Germania

Phone: +49 9721 784678
E-Mail: info@phs-memory.it
Web: www.phs-memory.it

All information without guarantee. Technical changes and errors excepted. You can find current price information in our online shop at <https://www.phs-memory.it>