
phs memory®

8GB Computer memory DDR3 for Fujitsu Primergy RX2520 M1 (D3169) RDIMM



PHS-memory® - computer memory with 100% quality

- many years of IT competence
- Free support for optimal configuration and product selection
- High availability through professional warehouse management
- Fast delivery in throughout Europe
- Short response times and professional order processing due to full digitalization throughout the entire process with complete traceability
- Incoming goods inspection include checks of the DRAMs, PCBs and the programmed SPDs in order to exclude possible errors (Controlled BOM).
- PHS-memory® brand memories guarantee 100% compatibility to the specified system.
- PHS-memory® memories can be used together with existing memories in the device depends on to the configuration rules of the system.
- The "fallback option" in the SPD of PHS-memory® allows DRAMs with higher clock rates to be operated together with older memory modules with lower clock rates within the system.
- Products with unique serial number for service and warranty
- Pre-sales and after-sales support by technically trained personnel



Memory Specification

4	133.35mm►		
DR3 RDIMM Warranty void if removed		17.3mm 9.5mm	30mm

Memory size	8GB			
Memory technology	DDR3			
ECC support	ја			
JEDEC Norm	PC3-10600R			
DRAM Organization	512Mx4			
Rank	2Rx4			
Туре	RDIMM (ECC Registered)			
Number of pins	240 Pin DIMM			
Memory data transfer rate	1333MHz @ CL9			
Speciality	-			
Board dimensions	133,35 x 30 (LxB mm)			
Operating temperature	0° C - 85° C			
Storage temperature	-40° C - +95° C			
RoHS compliant	Yes			
SKU	SP151134			
EAN	4055069244878			

Note: The module specified in this datasheet is one of several possible configurations available under this part number.

Some details may differ from the specifications described here and the illustration, but have no negative influence on the functionality.



System Specifications

The memory is 100% compatible with this sytem:

System manufacturer	Fujitsu
Device type	Server
Device family	Primergy
Device series	RX2500 Serie
Device name	Primergy RX2520 M1 (D3169)
Maximum memory*	384GB
Number of memory sockets	12
Annotation	ECC UDIMM, RDIMM and LR DIMM can not be mixed in the server. With ECC UDIMM a maximum of 48GB, RDIMM a maximum of 192GB, LR DIMM a maximum of 384GB is possible. For optimum performance, equip as many slots as possible with identical memory technology and capacity.

* The specifications for the maximum memory upgrade may differ from those of the manufacturer Fujitsu. Often the information given in the manual for the maximum memory upgrade is not up to date. New memory technologies, bios updates or newer software versions often allow the use of memory modules with a higher capacity than specified by the manufacturer with the same performance and stability.

Information on memory allocation

Information on memory configuration

The following technical specifications should be considered in advance:

- In the device, you can install RDIMM (Registered DIMM) or LRDIMM (Load Reduced DIMM) RAM memory modules. LRDIMM
 memory is recommended when aiming for large memory capacities.
- RDIMM memory modules cannot be used together with LRDIMM memories.
- If a memory expansion is to be used with existing RAM memories, it must be checked which memory technology (RDIMM / LRDIMM) is already installed in the device.
- Memory slots without a processor may not be used.
- A higher memory clock of the memory module automatically adapts to the memory clock specified by the system. This can be the case especially with larger capacities.

Information on memory installation

- Turn off the system
- Remove the plug of the power supply unit (if connected)
- Remove the battery, according to the user manual of the system



- Always ground yourself before touching electronic components
- Protect the memory module from static voltages:
 - Do not touch the gold pins of the memory module
 - Only touch the sides of the memory module
 - Use a grounding strap and/or ESD glove if possible

General installation instructions are supplied by E-Mail.



Further memory options for Fujitsu Primergy RX2520 M1 (D3169)

Size	SKU	Technology	Туре	Number of pins	Brand	Reference no.
4GB	SP151130	DDR3	UDIMM ECC (ECC unbuffered)	240 Pin DIMM	PHS-memory®	
8GB	SP465601	DDR3	UDIMM ECC (ECC unbuffered)	240 Pin DIMM	PHS-memory®	
8GB	SP151134	DDR3	RDIMM (ECC Registered)	240 Pin DIMM	PHS-memory®	
16GB	SP151132	DDR3	RDIMM (ECC Registered)	240 Pin DIMM	PHS-memory®	
32GB	SP151131	DDR3	LRDIMM (ECC LR DIMM)	240 Pin DIMM	PHS-memory®	
32GB	SP287766	DDR3	RDIMM (ECC Registered)	240 Pin DIMM	PHS-memory®	

PHS-memory® warranty

Every PHS-memory® is equipped with a 5-years-warranty of perfect operation. If the RAM module is defective or fails within 5 years of purchase when used properly, you will receive an appropriate RAM module free of charge. If a suitable memory module is no longer available, we will refund the purchase price.

For more information on warranty and service please visit https://www.phs-memory.it/-W5Y



Contact Information

PHS-electronic gmbh - www.phs-memory.it -Karl-Götz-Str. 5 97424 Schweinfurt Germania Phone: +49 9721 784678 E-Mail: info@phs-memory.it Web: www.phs-memory.it

All information without guarantee. Technical changes and errors excepted. You can find current price information in our online shop at https://www.phs-memory.it